



Online Guard Patrol User Manual

24.10.2013

1, Login	2
2, Create Users	3
3, Create Site	4-5
4, Entry tags	6-10
5, Set schedule	11-12
6, 8 kinds Reports	13-21
■ Detail Report	13-14
■ Statistics Report	15
■ Missed Report	16
■ Event Report	16
■ Impact, Low Battery Report	17
■ Flow Report	18
■ Upload Record Report	19
■ Login Log Report	19
7, Email	20-21
8, Setting	21
9, Choose software version	22
10, Other New function	23-25
11, Subscription	25



1, Login

1) Please login through www.onlineguardpatrol.com by your user name and password.

Online Guard Patrol (V1.20) Date Format: dd/MM/yyyy ▾

[Create shortcut](#) [Change Password](#)

Login

[Home](#) » [Login](#)

username *

password *

Remember me next time


follow OGP in APP

[number of patrol: 18968488](#) 

2) Modify the login password

vsdigital-security-company Online Guard Patrol (V1.20) Date Format: dd/MM/yyyy ▾

[Create shortcut](#) **[Change Password](#)**

[Home](#) [Data Entry](#) [Reader](#) [Report](#) [User](#) [Email](#) [Subscription](#) [Setting](#) [Logout \(bino\)](#) [Help](#)

Displaying 1-10 of 13 results.

Reader	Last Downloading Time	
1401-15970	17/07/2015 03:30:51	V1
1401-15971	17/07/2015 03:30:51	V1
1401-15972	17/07/2015 03:30:51	V1
1401-15973	17/07/2015 03:30:51	V1
1401-15978	17/07/2015 03:30:51	V1
1401-15974	17/07/2015 03:30:51	V1
1401-15976	16/07/2015 03:30:07	V1
1401-15977	16/07/2015 03:30:07	V1
Amy	15/07/2015 03:30:15	V1
1401-26423	21/05/2015 14:22:33	V1

Go to page: << First < Previous **1** 2 Next > Last >>

[number of patrol: 18968488](#) 



2, Create Users

1) Add a User/Client


1. Click **User**

2. Click  to add a user

3. Choose **Operator** or **Viewer**

4. 123456 is initial password for new users, if you want to modify it, re-login by new user name, then do it like “2) “

5. Click **Create**




The screenshot shows the 'User' management page of the Online Guard Patrol application. At the top, there is a navigation bar with the following items: Home, Data Entry, Reader, Report, **User**, Email, Subscription, Setting, Logout (bino), and Help. The 'User' menu item is highlighted in orange. Below the navigation bar, there is a breadcrumb trail: Home » User. The main content area displays a table of existing users with the following columns: User Name, Permissions, and Reset Password. The table contains three rows: Amy (Viewer), Tony (Operator), and bino (Viewer). Below the table, there are icons for deleting (trash) and adding (plus) users. The 'Add User' form includes a 'User Name *' field, a 'Permissions *' section with radio buttons for 'Operator' and 'Viewer' (the 'Viewer' option is selected and highlighted with a red box), and a text field for the initial password (123456). Below the form, there are 'Create' and 'Shrink' buttons. At the bottom of the page, there is a footer with the text 'number of patrol: 18970110' and a link to 'Download Communication Client' with a small logo.

User Name	Permissions	Reset Password
Amy	Viewer	
Tony	Operator	
bino	Viewer	



3, Create Site

- 1**, Click **Site**
- 2**, Click  to add a new route
- 3**, Fill in information
- 4**, Click **Create**



The screenshot shows the 'Online Guard Patrol' web application interface. At the top, there is a navigation menu with 'Data Entry' highlighted. A dropdown menu is open under 'Data Entry', with 'Site' selected and highlighted in red, labeled with a red '1'. Below the menu is a table with 3 rows and 4 columns: Name, Description, Contacts, and Tel. The table contains the following data:

Name	Description	Contacts	Tel
Patrol Site	Industrial Centre	Tom	19625 631234
Office building 2	rfid		
Test Centre	Evaluation	Jim	01234567789

Below the table, there is a trash icon and a plus icon in a red box, labeled with a red '2'. To the right of the plus icon is a form to create a new site, labeled with a red '3'. The form has the following fields:

- Name *
- Description
- Contacts
- Tel
- Mobile
- Address

At the bottom of the form, there are 'Create' and 'Shrink' buttons, with 'Create' highlighted in red and labeled with a red '4'. The footer of the page contains the text 'number of patrol: 18970126' and a 'Download Communication Client' button with a small icon.



Attention: If you want to modify the route information

1. Choose the route which is you want to modify
2. Re-write the information
3. Click **Update**

 vsdigital-security-company
Online Guard Patrol (V1.20) Date Format: dd/MM/yyyy ▾

[Create shortcut](#) [Change Password](#)

Home **Data Entry** Reader Report User Email Subscription Setting Logout (bino) Help

[Home](#) » [Patrol sites](#) Displaying 1-3 of 3 results.

<input type="checkbox"/>	Name	Description	Contacts	Tel
<input type="checkbox"/>	Patrol Site	Industrial Centre	Tom	19625 631234
<input type="checkbox"/>	Office building 2	rfd		
<input checked="" type="checkbox"/>	Test Centre	Evaluation	Jim	01234567789

Name *

Description

Contacts

Tel

Mobile

Address

number of patrol: 18970126  [Download Communication Client](#) 



4, Checkpoint, Event and Employee

■ **Add checkpoints**

1. Number all buttons in order



2. Read all buttons one by one orderly



3. Choose the route which you want to add checkpoint tags to

vsdigital-security-company
Online Guard Patrol (V1.20)

Date Format: dd/MM/yyyy

[Create shortcut](#) [Change Password](#)

Home **Data Entry** Reader Report User Email Subscription Setting Logout (bino) Help

[Home](#) » [Tag:Checkpoint](#)

Site Name: Patrol Site
All sites
Patrol Site
Office building 2
Test Centre

Displaying 1-2 of 2 results.

	Checkpoint ID	Name	Description	No.	
<input type="checkbox"/>	0085006B	1		1	
<input type="checkbox"/>	0085006B59F1	2		2	

[number of patrol: 18973136](#)

[Download Communication Client](#)

4. reader tags and upload, then click to add tags



5. Choose checkpoint tags which you want to add,

vsdigital-security-company
Online Guard Patrol (v1.20) Date Format: dd/MM/yyyy ▼

[Create shortcut](#) [Change Password](#)

Home **Data Entry** Reader Report User Email Subscription Setting Logout (bino) Help

Home » Tag:Checkpoint

Site Name: Displaying 1-2 of 2 results.

Checkpoint ID	Name	Description	No.	
<input type="checkbox"/> 0085006B7FAC	1		1	
<input type="checkbox"/> 0085006B59F1	2		2	

Displaying 1-200 of 216 results.

Category Name	Tag ID	Name	Description	Scan time
<input checked="" type="checkbox"/>	00000700082A27A	1 new tag		2014-11-13 16:05:49
<input checked="" type="checkbox"/>	0015004D7695	1 new tag		2014-11-15 15:21:36
<input type="checkbox"/>	0015004D7694	2 new tag		2014-11-15 15:21:41
<input type="checkbox"/>	0020003960B6	3 new tag		2014-11-15 15:23:31
<input type="checkbox"/>	00200039B3DC	4 new tag		2014-11-15 15:23:34
<input type="checkbox"/>	0020003960F6	5 new tag		2014-11-15 15:23:36
<input type="checkbox"/>	00200039B45D	6 new tag		2014-11-15 15:23:38

6. Click to add new checkpoint tags into the route which you selected

Attention: Tags which don't be added in **checkpoint tags**, these tags are called **no-register tags**, they are still in the report for you to use in the other part.



Online Guard Patrol (V1.23)

Home | **Data Entry** | Reader | Report | User | Email | Subscription | Setting | Logout (bino) | Help

Home » Tag:Checkpoint

Site Name:

Displaying 1-2 of 2 results

Checkpoint ID	Name	Description	No.
<input type="checkbox"/> 0085006B7FAC	1		1
<input type="checkbox"/> 0085006B59F1	2		2

Displaying 1-200 of 216 results

Category Name	Tag ID	Name	Description	Scan time
<input type="checkbox"/>	000000700082A27A	1 new tag		2014-11-13 16:05:49
<input type="checkbox"/>	0015004D7695	1 new tag		2014-11-15 15:21:36
<input type="checkbox"/>	0015004D7694	2 new tag		2014-11-15 15:21:41
<input type="checkbox"/>	0020003960B6	3 new tag		2014-11-15 15:23:31
<input type="checkbox"/>	00200039B3DC	4 new tag		2014-11-15 15:23:34
<input type="checkbox"/>	0020003960F6	5 new tag		2014-11-15 15:23:36

6. Click  to re- edit **Name** and **Description** of the checkpoint tag

7. Click   to adjust the position of the checkpoint.

Checkpoint ID	Name	Description	No.
<input checked="" type="checkbox"/> 01B37C70	1 new tag		1
<input type="checkbox"/> 01393B70	2 new tag		2
<input type="checkbox"/> 01706070	3 new tag		3

6

7

Checkpoint ID:

Name *:

Description:

6

Update Shrink

Attention: Use the same method mentioned above to add tags in the *Employee*.

■ Add events

Attention: events are used in event-wallet form. It supports copy when meet the same events in different event-wallet.


● Edit the name of events and event wallets

1. Click  to enter the event name



2. Click  to add event name which can be added more

3. Fill in the name of events and click **Create**



Home » Tag: Event

Site
Tag
Schedule
Checkpoint
Event
Employee

Displaying 1-10 of 1

	Description
<input type="checkbox"/>	Door is unlocked
<input type="checkbox"/>	Lock is broken
<input type="checkbox"/>	Light is on
<input type="checkbox"/>	Something is stolen
<input type="checkbox"/>	Computer is on
<input type="checkbox"/>	Air-container is on
<input type="checkbox"/>	Window is broken
<input type="checkbox"/>	CCTV is broken
<input type="checkbox"/>	Water pipe is broken
<input type="checkbox"/>	Machine is broken

Go to page: << First < Previous 1 2 Next >

  2

Name * 3
Description

Create Shrink

4. Click  to enter the event wallet

5. Click  to add event wallet which can be added more

6. Fill in the name of event wallets and click **Create**



Home » Tag: Event

Event Name
Event wallet

Displaying 1-1 of 1 result.

	Name	Description
<input type="checkbox"/>	first	

  5

Name * 6
Description

Create Shrink




•Add event tags

1. Choose the event wallet which wants to be added

2. Click  to add from no-register tags

3. Click  to add event tags

4. Click **Update** to save



Event Name Event wallet Displaying 1-5 of 13 results

	Name	Description
<input type="checkbox"/>	1	
<input type="checkbox"/>	2	
<input checked="" type="checkbox"/>	3	1
<input type="checkbox"/>	4	
<input type="checkbox"/>	5	

Go to page: << First < Previous **1** 2 3 Next > Last >>

Name *

Description

1 0010000313F9 Lock is broken Lock is broken ▾


2   Update Shrink

Download 216 ibuttons

	Button ID	Name	Descript	Category	Scan time
<input type="checkbox"/>	000000700082A27A	1 new tag			2014-11-13 16:05:49
<input type="checkbox"/>	0015004D7695	1 new tag	3		2014-11-15 15:21:36
<input type="checkbox"/>	0015004D7694	2 new tag			2014-11-15 15:21:41

•Copy Event Wallet

If names of two event wallets are same, you can choose one event wallet to copy , then click  (copy event wallet), click **Update**.



Name Description

<input type="checkbox"/>	1	
<input type="checkbox"/>	2	
<input checked="" type="checkbox"/>	3	
<input type="checkbox"/>	4	
<input type="checkbox"/>	5	

Go to page: << First < Previous **1** 2 3 Next > Last >>

Name *

Description

1 0010000313F9 Lock is broken Lock is broken ▾

  Update Shrink



5, Set schedule

1. Click **Schedule** to choose the route which you want to patrol
2. Click  to add a new schedule(the work day can be selected)
3. Fill out and click **Create**

Home » Schedule

Site Name: Patrol Site Office building 2 Test Centre

Displaying 1-7 of 7 results.

Site	Category	Start Time	End Time	Duration	patrolling times	Tolerance(min)	Working Day
Patrol Site	Daily	08:25	08:55	30(min)	1	5	MON TUE WED THU FRI SAT
Patrol Site	Daily	10:10	10:40	30(min)	1	5	MON TUE WED THU FRI SAT
Patrol Site	Daily	11:50	12:20	30(min)	1	5	MON TUE WED THU FRI SAT
Patrol Site	Daily	12:50	13:20	30(min)	1	5	MON TUE WED THU FRI SAT
Patrol Site	Daily	14:50	15:20	30(min)	1	5	MON TUE WED THU FRI SAT
Patrol Site	Daily	16:50	17:20	30(min)	1	5	MON TUE WED THU FRI SAT
Patrol Site	Daily	17:20	17:50	30(min)	1	5	SUN MON TUE WED THU FRI SAT

General

Category: Daily

Schedule start date: 2015/07/17 (YYYY-MM-DD)

Schedule end date: / / (YYYY-MM-DD)

Site: Patrol Site

Start time of daily: 00:00 (HH:MM)

End time of daily: 23:59 (HH:MM)

Start Time: 17:50 (HH:MM)

Duration: 30 (MM)

Tolerance: 5 (MM)

patrolling times: 1

Group management:

Set the patrolling time for every points

Working Day

Sunday

Monday

Tuesday

Wednesday

Thursday

Friday

Saturday

Create **Shrink**


Attention: If you choose “ Set the patrolling time for every points”, you could set time by yourself.



Here take 3 tags as an example:

Like checkpoint A is 7:00, B is 7:15, C is 7:30, Duration is 30, Tolerance is 10

- It is qualified to read A checkpoint tag from 06:50 to 07:10
- It is considered as overdue checkpoint from 6:45 to 6:50 or from 07:10 to 07:15(overdue is $\text{Duration}/2 = 30/2 = 15$)
- It is considered as an Missed checkpoint at other time



If

■ Copy Schedules

If you want to create a new schedule like this, just click  to copy the schedules from one to another.



6, Reports

Detail Report

Statistics Report

Missed Report

Event Report

Impact Report

Flow Report

uploadReport

Login Log

■ Detail Report

1. Check reports by month or site
2. Different colors and icons mean different events, click it to know more details.
3. If you want to know details of some date, click the date then you will see more details.

HomeData EntryReaderReportUserEmailNews subscriptionSettingLogout (bino)Online Help

[Home](#) » [Detail Report](#)

Detail Report

◀ [This month](#) ▶▶ 2015-06-01 ~ 2015-06-30

Site Name: Patrol Site ▼

2015-06-01 ~ 2015-06-30						
SUN	MON	TUE	WED	THU	FRI	SAT
	01	02	03	04	05	06
07	08	09	10	11	12	13
14	15	16	17	18	19	20
21	22	23	24	25	26	27
28	29	30				

Summary:

- [Event: 1](#)
- [Missed: 11](#)
- [Overdue: 0](#)
- Normal: 361



4. On the June 3, one tag missed, one event

2015-06-01~2015-06-30						
SUN	MON	TUE	WED	THU	FRI	SAT
	01	02	03	04	05	06
07	08	09	10	11	12	13
14	15	16	17	18	19	20
21	22	23	24	25	26	27
28	29	30				

Summary:

- [Event: 1](#)
- [Missed: 11](#)
- [Overdue: 0](#)
- Normal: 361

Plan date: 03/06/2015 00:00:00 ~ 03/06/2015 23:59:00

Schedule	08:25:00	10:10:00	11:50:00	12:50:00	14:50:00	16:50:00	17:20:00
1	08:25:00	10:10:00	11:50:00	12:50:00	14:50:00	16:50:00	17:20:00
2	08:39:00	10:23:00	12:14:00	13:02:00	15:11:00	17:05:00	
Summary							

Event:

Tag Name	Scan time	Employee		
Window is broken	03/06/2015 16:53:00	Chloe		


Missed:

Tag Name	Plan date	Plan time	Employee(as plan)	
2	03/06/2015	17:15:00~17:45:00		



■ Evaluation Chart Report

1. Check reports by Employee, Patrol Group, Checkpoint, Daily or Site
2. Choose what you want to compare
3. Know who is the best at a glance.





■ Missed Report

Chart with detail information of missed tags.

Home | Data Entry | Reader | Report | User | Email | News subscription | Setting | Logout (bino) | Online Help

[Home](#) » [Missed Report](#)

Missed Report

◀◀ [This month](#) ▶▶ 2015-07-01 ~ 2015-07-16

Site Name: All

Site Name	Missed times
Patrol Site	15
Office building 2	64
Test Centre	5

From:01/07/2015 00:00:00 To:16/07/2015 23:59:59
 Site Name: Patrol Site
 Missed times: 15

Tag Name	Plan time	Employee(as plan)
1	01/07/2015 08:20 ~ 09:00	
2	01/07/2015 08:20 ~ 09:00	
1	01/07/2015 10:05 ~ 10:45	
2	01/07/2015 10:05 ~ 10:45	
1	01/07/2015 11:45 ~ 12:25	

■ Event Report

Home | Data Entry | Reader | Report | User | Email | News subscription | Setting | Logout (bino) | Online Help

[Home](#) » [Event Report](#)

Event Report

◀◀ [This month](#) ▶▶ 01/07/2015 ~ 16/07/2015

Event: All Last CheckPoint Next CheckPoint

From:01/07/2015 00:00:00 To:16/07/2015 23:59:59
 Report created time:17/07/2015 10:41:42

Tag Name	Scan time	Site Name	Employee
Last CheckPoint:1	03/07/2015 14:50:00	Patrol Site	Nicole
Something is stolen	03/07/2015 14:53:00	Patrol Site	Nicole



■ Impact, Low Battery Report

You could know the reader is dropped during patrol time by Nicole

Home | Data Entry | Reader | Report | User | Email | News subscription | Setting | Logout (bino) | Online Help

Home » [Impact, Low battery Report](#)


Impact, Low battery Report

◀◀ [This month](#) ▶▶ 01/07/2015 ~ 16/07/2015

Reader Name: Impact Low battery

Low battery Report



Reader	Count
1401-15977	0
Amy	0
1401-15972	0
1401-15973	0
1401-15978	0
1401-15976	0
1401-15971	0
1401-15974	0
1409-51273	0
1308-16214	0
1404-19491	0
1401-26423	0
1401-15970	1

From: 01/07/2015 00:00:00 To: 17/07/2015 10:45:06
Report created time: 17/07/2015 10:45:06
Reader: 1401-15970

Scan time	Name	Taq ID	Employee
08/07/2015 13:33:00	Low battery	FFFFFFFFFFF9	Nicole



■ Flow Report

This report will show all patrol time, tags information according to your choice.

Home Data Entry Reader Report User Email News subscription Setting Logout (bino) Online Help

Home » Flow Report

Flow Report

2015-07-14 00:00:00 24 hour 1day 2days 1week Search

1month

Check by: Site All

- Site
- None
- Site
- Reader
- Employee

From: 14/07/2015 00:00:00 To: 14/07/2015 23:59:59
Check by: Site
Report created time: 17/07/2015 10:48:14
Site Name: Patrol Site

Total 1 result. | Total 14 results.

Scan time	Name	Tag ID	Description
14/07/2015 08:25:00	1	0085006B7FAC	
14/07/2015 08:54:00	2	0085006B59F1	
14/07/2015 10:10:00	1	0085006B7FAC	
14/07/2015 10:27:00	2	0085006B59F1	
14/07/2015 11:50:00	1	0085006B7FAC	
14/07/2015 12:00:00	2	0085006B59F1	
14/07/2015 12:50:00	1	0085006B7FAC	
14/07/2015 13:01:00	2	0085006B59F1	
14/07/2015 14:50:00	1	0085006B7FAC	
14/07/2015 15:02:00	2	0085006B59F1	
14/07/2015 16:50:00	1	0085006B7FAC	
14/07/2015 17:03:00	2	0085006B59F1	
14/07/2015 17:20:00	1	0085006B7FAC	
14/07/2015 17:48:00	2	0085006B59F1	




■ Upload Record Report

This report show which reader, when and how many tags are uploaded

Reader	Description	Upload Time	Uploading
1308-16214		13/11/2014 16:05:48	13
1401-15970		17/07/2015 03:30:51	58336
1401-15971		17/07/2015 03:30:51	60102
1401-15972		17/07/2015 03:30:51	55829
1401-15973		17/07/2015 03:30:51	59619
1401-15974		17/07/2015 03:30:51	63198
Amy		15/07/2015 03:30:15	58043
1401-15976		16/07/2015 03:30:07	56742
1401-15977		16/07/2015 03:30:07	55740
1401-15978		17/07/2015 03:30:51	55918
1401-26423		21/05/2015 14:22:33	460
1404-19491		31/01/2015 16:49:30	28
1409-51273		03/12/2014 09:08:12	444

■ Login Log Report


This report could show you who login this software, also could monitor all users.





7, Email

1. Click  to enter
2. Click  to add information of receive person



The screenshot shows the VSDIGITAL Online Guard Patrol web interface. At the top, there is a navigation menu with options: Home, Site, Tag, Schedule, Download, Reader, Report, User, Email (highlighted), Setting, and Logout (admin). Below the menu, there are two buttons: "Set Recipient" (with an envelope icon and a red box containing the number 1) and "Set Outbox" (with an envelope icon). Below these buttons is a table with three columns: "Email", "Contacts", and "Mobile". The "Email" column is selected. Below the table, there is a "No results found." message. To the left of the form is a trash can icon and a plus icon (with a red box containing the number 2). The form fields are: "Email *" (with the value "Jack@gmail.com"), "Contacts" (with the value "Jack"), and "Mobile" (with the value "123456789"). At the bottom of the form are "Create" and "Shrink" buttons.

3. Click  to set outbox(emails will be sent from this email)
4. Outbox server: the server of sending emails, only support SMTP agreement, please consult the supplier of this email service.
5. The function of testing email: In order to verify the email address is available or not, fill in the information, it means you set correctly if you can receive test email, or you should check it and fill in it again.



8, Set



9, Choose software version

- Low version: View the Flow Report, Event Report, Login Report and Upload Record Report
- Middle version : Set schedule, view the Detail Report, Evaluation Chart Report and Missed Report
- High version: adjustable schedule for each checkpoint, different sites can share one Checkpoint
- Professional version: Schedule is divided into daily, weekly, monthly and customized
- Shift Version: Daily only

vsdigital-security-company
Online Guard Patrol (V1.20)

Date Format: dd/MM/yyyy

[Create shortcut](#) [Change Password](#)

Home Data Entry Reader Report User Email Subscription **Setting** Logout (bino) Help

[Home](#) » [Setting](#)

Company vsdigital-security-company

Software Version Low Ver Middle Ver High Ver Professional Shift Ver

Data Retain 24 month(1~24)

BackUp Cycle 30 Days(7~300)

BackUp Path D:\OGPBack

Save

Data BackUp

[number of patrol: 18963202](#)

[Download Communication Client](#)




10, Other New function

1) public point in the routes (or crossing point)

Different routes can use the same checkpoint.

Method:

- 1, Choose the route which will be added
- 2, Click  (choose add from other route)
- 3, Choose one route to add
- 4, Choose place which will be added
- 5, Click  to add



The screenshot shows the 'Tag' section of the VSDIGITAL Online Guard Patrol interface. The site name is set to 'the second floor of building'. A table of checkpoints is displayed, with 'No results found.' shown. Below the table, there are icons for adding a new checkpoint, and a dropdown menu for selecting a route. The dropdown menu is set to 'the first floor of building'. A table of routes is displayed, with 'room', 'room 1', and 'room 2' listed. The 'room' row is selected. A plus icon is visible at the bottom left of the interface.

Checkpoint ID	Name	Description	No.
014D6C6F	room		
01714C70	room 1		
011E3370	room 2		

2) teams

patrol teams: can set several teams, people can have one person or several person.

- 1, Click **Tag** and **Employee**
- 2, Click  to add teams
- 3, Click  to add
- 4, Fill the information
- 5, Click **Create**



VSDIGITAL Online Guard Patrol (V1.10) 59 days remaining for network features

Date Format: yyyy-MM-dd

Home Site **Tag** (1) Schedule Download Reader Report User Email Setting Logout (admin)

Home > Tag: Employees

Group management (2) Employee management

Displaying 1-2 of 2 results.

<input type="checkbox"/>	Name	Description
<input type="checkbox"/>	Group 1	
<input type="checkbox"/>	Group 2	

Group management actions: (3) Create, Shrink

Create form: Name: Group 3 (4), Description: []

Create button: (5)

3) Set patrol time point by point

Schedule can adjust patrol time point by point, and can bind teams or patrolmen.

When there is a intersection point in different routes, schedule must appoint team or patrolman, or lead to wrong patrol data.

- 1.** Click **Schedules**
- 2.** Choose the route
- 3.** Choose Group
- 4.** Choose **Set the scan time for every points**
- 5.** Set time
- 6.** Click **Update**



VSDIGITAL Online Guard Patrol (V1.10) 59 days remaining for network features

Date Format: yyyy-MM-dd

Home Site Tag **Schedule** Download Reader Report User Email Setting Logout (admin)

Home » Schedule

Site Name: the first floor of building

Displaying 1-1 of 1 result.

<input checked="" type="checkbox"/>	Site	Start Time	Duration(min)	Tolerance(min)	Working Day
<input checked="" type="checkbox"/>	the first floor of building	11:30	35	5	SUN MON TUE WED THU FRI SAT

General

Site: the first floor of building

Start Time: 11:30 (HH:MM)

Duration: 35 (MM)

Tolerance: 17.5 (MM)

Group management: Group 1 None

Set the scan time for every points

room: 11:30

room 1: 11:47

room 2: 12:05

Working Day

- Sunday
- Monday
- Tuesday
- Wednesday
- Thursday
- Friday
- Saturday

Update Shrink

11, Subscription

This is used for APP mobile tour management platform, you could choose which messages you want to send to your phone.

Home Data Entry Reader Report User Email **Subscription** Setting Logout (bino) Help

Home » Subscription

Save

related sites to me

- Patrol Site
- Office building 2
- Test Centre

related events to me

- reader was impacted
- reader is low power
- Door is unlocked
- Lock is broken